

APP EV Charger Pillar 16A/32A Outlet

This is an app APP EV Charger Pillar 16A/32A outlet and suitable for house, shopping mall and car parking use. The app APP EV Charger Pillar 16A/32A outlet is easy to install, stable in performance and has a complete protection mechanism. The LCD display of the APP EV Charger Pillar 16A/32A outlet can show the detailed charging status. WOCOR[®] look forward to becoming your long-term APP EV Charger Pillar 16A/32A outlet partner in china.

Product Description

APP EV Charger Pillar 16A/32A outlet- Max 22KW-20feet cable with CCS2(type2)/J1772(type1) plug

This is a APP EV Charger Pillar 16A/32A outlet and suitable for shopping center, car parking and service station use. It is easy to install, stable in performance, and has a complete protection mechanism. The APP EV Charger Pillar 16A/32A outlet's LCD display can show the detailed charging status. The charger can be used with stand.

- 1.Do not connect the circuit by yourself without professional guidance
- 2.Do not use the charger when the inside of the plug is wet
- 3. Do not install the charger by yourself before reading the instructions.
- 4. Do not use the charger for other purposes except for electric car charging

This APP EV Charger Pillar 16A/32A outlet is the latest invention and have high-quality CE certification. The APP EV Charger Pillar 16A/32A outlet body box is made of Aluminum alloy+Acrylic, which has been designed to prevent the product from overheating during use of safety problems and indication of working status very well. The APP EV Charger Pillar 16A/32A outlet is a basic wall-mount charger and suitable for shopping malls,office properties and service stations. The charger can be used with wall hanging.

The specifications of (32A/6A 7KW 11KW 22KW) with APP EV Charger Pillar 16A/32A outlet can be OEM/ODM according to your needs. APP EV Charger Pillar 16A/32A outlet combines with 5m electric cable, a charging box, an electric gun and a pillar. There an European standard of the APP EV Charger Pillar 16A/32A outlet 16A/32A outlet electric guns.



Product Parameters			
Electrical Specification		Working Environment	
AC input voltage	230VAC20%/AC380V+10%	Protection degree	165
AC power frequency	50-60 Hz	Environment temperature	-30%~55%
Nominalpower	7KW11KW 22KW	Relative humidity	5%-95% non-condensing
Output rated current		Maximum altitude	<2000m
Charging interface type		Standby power	<4W